



# EWEB Lighting Program Offerings

March 2026

An application is required. Rebates totaling over \$2,500 must be pre-approved by EWEB.

- LEDs replacing fluorescent lighting are no longer eligible for prescriptive incentives as of Oct 1, 2025. The sale of fluorescent lamps is banned in Oregon as of Jan 1, 2025. A possible exception exists for K-12 school districts or if the new LEDs are more efficient than code, check with EWEB for details.
- Rebates are capped at 50 percent of project costs and/or capped at \$0.50/kWh for any calculated measures. The maximum rebate amount for an individual project is \$50,000.
- Installed LED lighting equipment must meet at least one of the following three criteria:
  - [DesignLights Consortium® \(DLC\)](#)
  - [ENERGY STAR®](#)
  - Have a minimum efficacy of 90 lumens per Watt, a minimum warranty of 5 years, and EWEB approval
- Horticulture lighting ONLY - Installed LED lighting equipment must meet at least one of the following two criteria:
  - [DesignLights Consortium® \(DLC\)](#)
  - Have a minimum efficacy of 1.9 umol/J, a minimum warranty of 5 years, and EWEB approval
- The Total Resource Cost (TRC) benefit-to-cost ratio must be greater than 0.50 (TRC > 0.50) for projects saving greater than 200,000 kilowatt-hours (kWh).
- Total project kWh savings must be greater than 10 percent of the baseline equipment consumption.

## Measure Series A: LED Small Lamps and Fixtures \*

Measure Series A covers interior and exterior Light-Emitting Diode (LED) small lamps and fixtures including:

- Parabolic Aluminized Reflector (PAR)
- Bulged Reflector (BR)
- A-lamps
- Multifaceted Reflector (MR)
- Recessed cans or kits
- Other medium base LED screw-in or small fixture variations

| Measure | Watt Baseline | Required Wattage Reduction | Incentive Per Lamp |
|---------|---------------|----------------------------|--------------------|
| A1-40%  | ≤100          | ≥40%                       | \$3                |
| A2-40%  | ≥101          | ≥40%                       | \$6                |

Notes:

- ❖ Refer to Measure Series F for screw-in LED products replacing high-intensity discharge (HID) lamps.
- ❖ Existing incandescent lamps are not eligible for replacement.

## Measure Series B and O: LED Tubes \* (Note: not available in Oregon)

Measure Series B covers Type A LED Tubes (TLEDs).

Measure Series O covers Type B and Type C LED Tubes.

These series include:

- 4 feet
- 8 feet
- Irregular length
- U-bend

| Measure | Watt Baseline | Required Wattage Reduction | Incentive Per Lamp |
|---------|---------------|----------------------------|--------------------|
| B1-30%  | ≥1            | ≥30%                       | \$2                |
| O1-30%  | ≥1            | ≥30%                       | \$9                |

## Measure Series C: LED General Indoor and Outdoor \*

Measure Series C covers a variety of fixtures typically installed under 15 feet including:

- Recessed troffers
- Surface mounted wraps
- Vapor tights
- Other similar linear fixtures

This category excludes exterior applications such as parking lots, wall packs, roadways, and similar areas. For these applications, refer to Measure Series E: LED Exterior.

| Measure | Watt Baseline | Required Wattage Reduction | Incentive Per Standard Fixture |
|---------|---------------|----------------------------|--------------------------------|
| C1-40%  | ≤100          | ≥40%                       | \$22                           |
| C1-50%  | ≤100          | ≥50%                       | \$33                           |
| C1-60%  | ≤100          | ≥60%                       | \$44                           |
| C1-70%  | ≤100          | ≥70%                       | \$55                           |
| C2-40%  | 101-200       | ≥40%                       | \$44                           |
| C2-50%  | 101-200       | ≥50%                       | \$66                           |
| C2-60%  | 101-200       | ≥60%                       | \$88                           |
| C2-70%  | 101-200       | ≥70%                       | \$110                          |
| C3-40%  | ≥201          | ≥40%                       | \$77                           |
| C3-50%  | ≥201          | ≥50%                       | \$110                          |
| C3-60%  | ≥201          | ≥60%                       | \$132                          |
| C3-70%  | ≥201          | ≥70%                       | \$154                          |

Notes:

- ❖ Hard-wired recessed can fixtures may be entered under Measure Series C: General Indoor and Outdoor.

## Measure Series D: LED High Bay \*

Measure Series D covers interior LED high-bay fixtures.

| Measure | Watt Baseline | Required Wattage Reduction | Incentive Per Fixture |
|---------|---------------|----------------------------|-----------------------|
| D1-40%  | 140-299       | ≥40%                       | \$88                  |
| D1-60%  | 140-299       | ≥60%                       | \$154                 |
| D1-70%  | 140-299       | ≥70%                       | \$220                 |
| D2-40%  | 300-399       | ≥40%                       | \$110                 |
| D2-60%  | 300-399       | ≥60%                       | \$198                 |
| D2-70%  | 300-399       | ≥70%                       | \$330                 |
| D3-40%  | 400-499       | ≥40%                       | \$154                 |
| D3-60%  | 400-499       | ≥60%                       | \$264                 |
| D3-70%  | 400-499       | ≥70%                       | \$396                 |
| D4-40%  | ≥500          | ≥40%                       | \$275                 |
| D4-60%  | ≥500          | ≥60%                       | \$440                 |
| D4-70%  | ≥500          | ≥70%                       | \$550                 |

Notes:

- ❖ LED Screw-in products replacing HID are not eligible for the high bay category and must be entered in Measure Series F: HID Replacement Screw-in.

## Measure Series E: LED Exterior \*

Measure Series E covers exterior LED applications including:

- Parking lot
- Parking garage
- Roadway
- Wall packs
- Bollards
- Floods
- Barn and yard
- Pole lamps
- Canopy
- High mast

| Measure | Watt Baseline | Required Wattage Reduction | Incentive Per Fixture |
|---------|---------------|----------------------------|-----------------------|
| E1-40%  | 30-99         | ≥40%                       | \$33                  |
| E1-60%  | 30-99         | ≥60%                       | \$44                  |
| E1-70%  | 30-99         | ≥70%                       | \$55                  |
| E2-40%  | 100-199       | ≥40%                       | \$66                  |
| E2-60%  | 100-199       | ≥60%                       | \$88                  |
| E2-70%  | 100-199       | ≥70%                       | \$110                 |
| E3-40%  | 200-299       | ≥40%                       | \$88                  |
| E3-60%  | 200-299       | ≥60%                       | \$132                 |
| E3-70%  | 200-299       | ≥70%                       | \$154                 |
| E4-40%  | 300-399       | ≥40%                       | \$110                 |
| E4-60%  | 300-399       | ≥60%                       | \$198                 |
| E4-70%  | 300-399       | ≥70%                       | \$275                 |
| E5-40%  | 400-499       | ≥40%                       | \$132                 |

March 2026

|        |         |      |       |
|--------|---------|------|-------|
| E5-60% | 400-499 | ≥60% | \$242 |
| E5-70% | 400-499 | ≥70% | \$330 |
| E6-40% | ≥500    | ≥40% | \$275 |
| E6-60% | ≥500    | ≥60% | \$440 |
| E6-70% | ≥500    | ≥70% | \$550 |

Notes:

- ❖ Refer to Measure Series F for screw-in LEDs replacing existing HID lamps.
- ❖ General service fixtures such as vapor tights or surface mounted wraps installed in exterior applications should be entered using Measure Series C General Indoor and Outdoor.

## Measure Series F: HID Screw-in Replacement

The HID Screw-in Replacement Measure Series covers all mogul and medium base LED products which are replacing existing HID lamps. This measure series shall be selected whenever a screw-in LED product is replacing an HID.

| Measure | Watt Baseline | Required Wattage Reduction | Incentive Per Lamp |
|---------|---------------|----------------------------|--------------------|
| F1-40%  | 40-200        | ≥40%                       | \$22               |
| F2-40%  | 201-300       | ≥40%                       | \$44               |
| F3-40%  | 301-400       | ≥40%                       | \$66               |
| F4-40%  | 401-999       | ≥40%                       | \$88               |
| F5-40%  | ≥1000         | ≥40%                       | \$165              |

Notes:

- ❖ Measure Series F applies to both mogul-base and medium-base screw-in products whenever they are replacing existing HID lamps.

## Measure Series G: LED Linear \*

Measure Series G covers interior and exterior linear LED applications including:

- Refrigerator case lights
- Accent lighting
- Cove lighting

| Measure | Watt Baseline | Required Wattage Reduction | Incentive Per kWh Saved |
|---------|---------------|----------------------------|-------------------------|
| G1      | N/A           | N/A                        | \$0.15                  |

Notes:

- ❖ Refer to Measure Series J for sign applications.

## Measure Series H: LED Exit Signs \*

Measure Series H covers all LED exit signs.

| Measure | Watt Baseline | Required Wattage Reduction | Incentive Per Installed Fixture |
|---------|---------------|----------------------------|---------------------------------|
| H-90%   | 10-100        | ≥90%                       | \$22                            |

Notes:

- ❖ When selecting LED exit signs, the annual hours of operation are automatically set to 8,760.

## Measure Series I: Signage \*

Measure Series I covers all exterior sign applications.

| Measure | Watt Baseline | Required Wattage Reduction | Incentive Per kWh Saved |
|---------|---------------|----------------------------|-------------------------|
| I1      | N/A           | N/A                        | \$0.15                  |

Notes:

- ❖ Measure Series I is a calculated incentive and does not require pre-approval.

## Measure Series J: Decommissioning and Fixture Increase \*

Measure Series J covers both decommissioning and fixture increases. These measures are automatically recognized by the lighting calculator and receive a calculated incentive.

Decommissioning projects must:

- Achieve at least 10 percent net energy savings
- Qualify for a minimum incentive of \$5.00 to receive a payout

Fixtures must be completely removed (not just disconnected) to qualify. BPA does not require removal of conduit leading to the fixture.

| Measure | Watt Baseline | Required Wattage Reduction | Incentive Per kWh Saved |
|---------|---------------|----------------------------|-------------------------|
| J1      | N/A           | N/A                        | \$0.15                  |

## Measure Series K: Non-Standard Measures \*

Measure Series K is used when existing or proposed equipment is not available in the lighting calculator's dropdown options or when prompted to enter a non-standard measure.

To qualify non-standard measures must:

- Achieve at least 10 percent net energy savings
- Qualify for a minimum incentive of \$5.00 to receive a payout

| Measure | Watt Baseline | Required Wattage Reduction | Incentive Per kWh Saved |
|---------|---------------|----------------------------|-------------------------|
| K1      | N/A           | N/A                        | \$0.15                  |

Notes:

- ❖ Required: Non-standard measures must be submitted to the utility for approval.

## New Construction

| Measure | Watt Baseline | Required Wattage Reduction | Incentive Per kWh Saved |
|---------|---------------|----------------------------|-------------------------|
| NC      | N/A           | N/A                        | \$0.15                  |

## Measure Series L: Controls

Measure Series L covers occupancy sensors and multi-functional controls. Multi-functional controls are defined as controls which can operate and are commissioned beyond a simple binary function.

| Measure                              | Required Range (Watts) | Incentive Per Control |
|--------------------------------------|------------------------|-----------------------|
| L1-Occupancy Sensor                  | 15-44                  | \$11                  |
|                                      | 45-200                 | \$33                  |
|                                      | ≥201                   | \$55                  |
| L2-Multi-Function                    | 15-44                  | \$17                  |
|                                      | 45-200                 | \$44                  |
|                                      | ≥201                   | \$55                  |
| L3-Other                             | 15-44                  | \$11                  |
|                                      | 45-200                 | \$33                  |
|                                      | ≥201                   | \$44                  |
| L4-Luminaire Level Lighting Controls | 15-44                  | \$50                  |
|                                      | 45-200                 | \$75                  |
|                                      | ≥201                   | \$150                 |

### Notes:

- ❖ Controls in Measure Series L receive an automatic 25 percent reduction on operating hours. Users may adjust this number with utility consent.
- ❖ Luminaire Level Lighting Controls must be on DLC Network Lighting Control (NLC) QPL.

### \*

LEDs replacing fluorescent lighting are no longer eligible for prescriptive incentives as of Oct 1, 2025. The sale of fluorescent lamps is banned in Oregon as of Jan 1, 2025. A possible exception exists for K-12 school districts or if the new LEDs are more efficient than code, check with EWEB for details.